



Workshop Manual CityCat 5006

BUCHER
municipal

Display Software update

In case of Bucher Municipal Customer service request to perform an update with new OS version for Node 1 and 2, please follow the procedure described below:

1. Preparation of the USB Memory stick

- Memory stick "part number 7014159" must be fully empty
- Fill up the memory stick with data set release by Bucher Municipal customer service like described at the view below "**Please do not change the layout of data**".
- Insert the memory stick in the display.

| File Name | File Type | Modified | Size |
|---------------------|-----------------------|---------------------|-----------|
| OS | Folder | | |
| autocopy.ini | Paramètres de conf... | 06.07.2016 15:10:48 | 1,122 |
| autorstart.bat | Fichier de command... | 06.07.2016 15:10:48 | 863 |
| bootupscreen.bmp | Image bitmap | 11.09.2014 09:22:22 | 385,080 |
| bootupscreen_n... | Image bitmap | 11.09.2014 10:02:16 | 768,056 |
| FMC01_1.11.0... | Fichier OS | 18.07.2012 17:22:22 | 312,376 |
| FMC01_1.20.1.0... | Fichier OS | 10.08.2012 10:26:10 | 1,137,064 |
| ion.os | Fichier OS | 08.06.2016 14:49:30 | 60,272 |
| ion.os.txt | Document texte | 08.06.2016 14:49:30 | 9 |
| ISO_library_7E... | Fichier LB3 | 28.07.2014 14:15:16 | 2,117 |
| iso_library_jym4... | Fichier LB3 | 21.01.2014 11:06:24 | 2,342 |
| JetViewERS.cfg | Fichier CFG | 23.01.2014 17:51:02 | 637 |
| JetViewERS_new... | Fichier CFG | 28.07.2014 14:15:16 | 637 |
| ngs_4m3_bs.es3 | Fichier ES3 | 06.07.2016 10:38:46 | 223,370 |
| NGS_4m3_BS.iop | Fichier IOP | 05.07.2016 15:06:08 | 3,150,603 |
| ngs_4m3_bs_ne... | Fichier ES3 | 06.07.2016 10:34:32 | 222,759 |
| start.ini | Paramètres de conf... | 06.07.2016 15:10:48 | 62 |

2. Insert the memory stick in the display

3. Press F1 and F3 and hold F1 and F3 until the indications of loading process appear on the screen.

4. Turn ON the ignition key of the sweeper

5. When the loading process appear on the display release F1 and F3.

6. During the loading process please don't press any functions on the display.

7. End of loading process the display make an automatic new start up.

8. Press the Knob **MENU**, select and press **⏏** and select **🖨** and checked if the display SW shows last version with G for example like the view below.



Press F4 to go out.